

Type JA

Shaded area denotes obsolete or discontinued products and services. ^①

JA: 600 Vac; 250 Vdc



Type JA 70–225A, 600 Vac, 250 Vdc, Two- and Three-Pole, Fixed Trip, Thermal-Magnetic, Saf-T-Vue (Suitable for Reverse-Feed)

Continuous Ampere Rating at 40°C	Magnetic Trip Setting, Amperes (Set on High Side, Adjustable to Lower Limits)		Complete Breaker Includes Pressure Type Aluminum Terminals ^②		Breaker Without Terminals	
	Low	High	Standard Catalog Number	Saf-T-Vue Catalog Number	Standard Catalog Number	Saf-T-Vue Catalog Number
Two-Pole, 600 Vac, 250 Vdc ^③						
70	350	700	JA2070	JA2070S	JA2070W	JA2070SW
90	450	900	JA2090	JA2090S	JA2090W	JA2090SW
100	500	1000	JA2100	JA2100S	JA2100W	JA2100SW
125	625	1250	JA2125	JA2125S	JA2125W	JA2125SW
150	750	1500	JA2150	JA2150S	JA2150W	JA2150SW
175	875	1750	JA2175	JA2175S	JA2175W	JA2175SW
200	1000	2000	JA2200	JA2200S	JA2200W	JA2200SW
225	1125	2250	JA2225	JA2225S	JA2225W	JA2225SW
Approx. shipping weight 12 lbs					Approx. shipping weight 12 lbs	

Three-Pole, 600 Vac Only

70	350	700	JA3070	JA3070S	JA3070W	JA3070SW
90	450	900	JA3090	JA3090S	JA3090W	JA3090SW
100	500	1000	JA3100	JA3100S	JA3100W	JA3100SW
125	625	1250	JA3125	JA3125S	JA3125W	JA3125SW
150	750	1500	JA3150	JA3150S	JA3150W	JA3150SW
175	875	1750	JA3175	JA3175S	JA3175W	JA3175SW
200	1000	2000	JA3200	JA3200S	JA3200W	JA3200SW
225	1125	2250	JA3225	JA3225S	JA3225W	JA3225SW
Approx. shipping weight 14 lbs					Approx. shipping weight 12 lbs	

Special Breakers ^④

Continuous Ampere Rating at 40°C	Magnetic Trip Setting, Amperes (Set on High Side, Adjustable to Lower Limits)		Two-Pole ^④		Three-Pole	
	Low	High	Standard Catalog Number	Saf-T-Vue Catalog Number	Standard Catalog Number	Saf-T-Vue Catalog Number
Magnetic Only Breakers, Front Adjustable—Without Terminals ^⑤						
225	350	700	JA2700MW	JA2700SMW	JA3700MW	JA3700SMW
225	625	1250	JA21250MW	JA21250SMW	JA31250MW	JA31250SMW
225	750	1500	JA21500MW	JA21500SMW	JA31500MW	JA31500SMW
225	875	1750	JA21750MW	JA21750SMW	JA31750MW	JA31750SMW
225	1125	2250	JA22250MW	JA22250SMW	JA32250MW	JA32250SMW

Ambient Compensating Breakers

70	350	700	JA2070A	—	JA3070A	—
100	500	1000	JA2100A	—	JA3100A	—
125	625	1250	JA2125A	—	JA3125A	—
150	750	1500	JA2150A	—	JA3150A	—
175	875	1750	JA2175A	—	JA3175A	—
200	1000	2000	JA2200A	—	JA3200A	—
225	1125	2250	JA2225A	—	JA3225A	—

Notes

^① These frames are obsolete. For replacement solutions, see the cross-reference on **Pages V12-T3-114–V12-T3-167**.

^② Terminals are shipped separately from breaker frame.

^③ Not UL Listed.

^④ Two-pole breakers are supplied in three-pole frames with current carrying parts omitted from center pole.

^⑤ Select desired terminal from table and order as separate item.